




NECD LED DOWNLIGHT



NECD LED DOWNLIGHT




CDG-K1004


Input Voltage	700mA max, 8-10.5V
LED Current	DC350mA
Light Source	CREE(XPE)
Power	3W & 9W
CCT	3000K
Beam Angle	60°
Operation Temperature	-4°F – + 122°F
Lamp Working Temperature	≤140°F
Life-Span	50,000 Hours
CRI	>80
Surface Color	Silver <i>(Custom Paint Colors Available)</i>
Cutout Size	Φ 2.75 in

Power Supply Required — SK-CAB XXXXXX


NECD LED DOWNLIGHT



CEILING MOUNT (HORIZONTAL)



CAB TOP MOUNT (VERTICAL)



ELEVATOR CAB LIGHTING

The SK-CAB battery backed cab lighting system was designed to provide an intelligent efficient LED based lighting solution for elevator cabs. In the event of a power outage, it also incorporates an emergency battery back up system to provide power for lights and a cab-operated alarm.

Features:

- Dimming input with on/off and 8 brightness settings.
- External light switch input.
- 30-month battery life indication.
- 3W and 9W models available.
- When activated in Emergency Power condition 2 of the Led Lamps are turned on using CE's Intelli-Socket design.
- This Intelli-Socket design monitors all circuits for Loads and keeps two of the Led's on while activated meeting ASME A17 code.
- Incorporates intelligent load software.
- Options for: 6V, 12V, and 24V alarm drivers.
- Optional: Sonalert Alarm added
- Top of cab or ceiling-mount / clam shell options available.



- Optional: SKDIM remote dimmer feature available

Battery backup mode provides emergency power for:

- 2 lamps powered for 4 hours. Unit will automatically power two lamps. If the designated lamp socket is empty or a lamp burns out, a new lamp will be turned on.
- 1 bell powered for 1 hour. 80-90 DBA @ 3 meters

TO ORDER:-SPECIFY SKCAB - X X X X X X

WATTS:

"03" = 3 WATTS - 6, 9 or 12 LAMP
"09" = 9 WATTS - 6 or 9 LAMP MAX
"ME" = MR16/E27

NUMBER OF LAMP OUTPUTS

"06" = 6 LAMPS
"09" = 9 LAMPS
"12" = 12 LAMPS - 3WATT ONLY

"X" = BATTERY ONLY


"A" = 6V OUTPUT - NO BELL INCLUDED
"B" = 12V OUTPUT - NO BELL INCLUDED
"C" = 24V OUTPUT - NO BELL INCLUDED
"D" = SONALERT ADDED
"Z" = NO BATTERY

BOX:

"H" = HORIZONTAL / CLAM SHELL
"V" = VERTICAL / TOC

NECD LED DOWNLIGHT

3W



9W

